FORD CONNECTED CHARGE STATION

The Wi-Fi and Bluetooth® enabled Ford Connected Charge Station can charge:

- Ford F-150 Lightning® Truck at an average of 20 miles of range per charging hour with an extended-range battery.*
- Mustang Mach-E® at an average rage of 27 miles of range per charging hour with an extended-range battery.*
- From 12-48 Amp as needed for the load management available in main panel.



DETAILS

- CIRCUIT BREAKER
 15-60A Select based on Work Ampere setting, see
 Installation Guide. (Do NOT use GFCI breaker since internal GFCI is included and false tripping will occur.)
- VOLTAGE 240 VAC nominal, 2 poles, 60 Hz.
- TWO OPTIONS FOR WIRE CONFIGURATIONS

 (1) Three-wire configuration of L1, L2, and Ground or(2) flexible four-wire configuration (for future removal and replacement with a NEMA 14-XX outlet) of L1, L2, Ground, and Neutral hardwired to junction box.
- CONDUCTORS
 Follow local and national codes/regulations.
- VENTILATION Not required.
- INSTALLATION LOCATION
 Between 35" and 60" from ground to device midpoint.NEMA
 35 Waterproofing for outdoor or indoor installation
- DIMENSIONS 258mm x 450mm x 131 mm (W x H x D).
- CONNECTED SETUP
 Download Ford Connected Charge Station Setup App and follow the prompts.
- WI-FI ENABLED Ensure home Wi-Fi signal reaches planned location.

Referenece the Installation Guide for futher details.

OTHER RESOURCES

QUESTIONS/ASSISTANCE?

Ford Customer Relationship Center: 1-800-392-FORD (3673)

For more details and specifications on the Ford Connected Charge Station (48 amp) visit https://chargers.ford.com.

Qmerit is Ford's recommended installation partner. Please visit https://gmerit.com/ev/ford/ and complete the online self-assessment.

- Plug the Ford Connected Charge Station cord set coupler into the vehicle charge port.
- 2. Download the Ford Charge Station Setup App and follow prompts.
- If you do not download the setup app, your vehicle will charge when plugged in (unless it is outside of prescheduled charge times), but the connected features will not be available.



